

### Models Available

7251  
7251A

### 200 Series Bases

B501(A)	Flangeless Mounting Base
B210LP(A)	Flanged Mounting Base
B501BH(A)	Standard Sounder Base
B501BHT(A)	Temporal Tone Sounder Base
B224RB(A)	Relay Base
B224BI(A)	Isolator Base
SMK400	Flangeless Surface Mounting Kit
SMB600	Flanged Surface Mounting Kit

### 200 Series Accessories

RA400Z(A)	Remote LED Annunciator
M02-04-01	Detector Test Magnet
M02-09-00	Telescoping Test Magnet
XR-2	Detector Removal Tool
XP-4	Extension for XR-2 (5-15 ft.)
DUST12	Dust Cover

(A) suffix denotes Canadian products

7251 with B210LP Flanged Mounting Base



7251 with B501 Flangeless Mounting Base

### Product Overview

#### Ultra-high-sensitivity capability

#### On-board drift compensation

#### Transient rejection algorithms

#### Environmental tracking

#### Wide sensitivity range

#### Rotary address switches

#### Analog communications

#### Sleek, low-profile design

#### Low standby current

#### Microprocessor design

#### Superior EMI protection

Pinnacle™ model 7251 is an intelligent, laser-based photoelectric smoke detector featuring extensive on-board signal processing capabilities designed to improve smoke response. Pinnacle also features a patented smoke sensing chamber, designed to amplify signals from smoke, but diminish stray internal reflections. By using a laser diode instead of a standard LED light source into the sensing chamber, Pinnacle is able to achieve sensitivities from 0.02% to 2% per foot obscuration.

The detectors' extensive software processing includes multi-alert drift compensation, internal self diagnostics, and superior transient signal rejection algorithms to produce unprecedented stability at ultra high sensitivities, over the complete temperature range.

Because Pinnacle is base-compatible with all other 200 Series detectors, system designers can seamlessly mix it with other standard detection technologies thereby reducing overall cost.

Other advantages of Pinnacle over other high sensitivity detection methods are:

- Pinpoint identification of the fire location resulting from addressability.
- No delay in response because of smoke dilution or smoke transportation time as in aspirated systems.
- Complete supervision of wiring and detector

Pinnacle is designed to protect valuable assets and operations where systems must remain on-line at all times. Many sensitive areas cannot tolerate even small amounts of smoke. Some ideal applications for Pinnacle include:

- Telecommunications switching facilities
- Cellular telephone infrastructure
- Integrated circuit fabrication facilities
- Computer rooms
- Traffic control centers
- Clean rooms



## Specifications

### Voltage Range

15 – 32 volts DC peak

### Standby Current (max. avg.)

230  $\mu$ A @ 24 VDC

(without communication),

330  $\mu$ A @ 24 VDC (one communication every 5 sec. with LED enabled)

### LED Current (max.)

6.5 mA @ 24 VDC (on)

### Height

1.66" (4.2 cm)

### Diameter

4.0" (10.2 cm)

### Shipping Weight

5.6 oz. (159 g)

### Operating Temperature Range

32° to 100°F (0° to 38°C)

### Velocity Range

0 – 4000 fpm (0 to 20.3 m/s)

### Relative Humidity

10% – 93% noncondensing

### Self Diagnostics

Initiated by control panel

Activated by test magnet

### Smoke Sensitivity

9 levels:

0.02, 0.03, 0.05, 0.10, 0.20, 0.50, 1.00, 1.50, 2.00%/ft. obscuration

(0.06, 0.10, 0.16, 0.33, 0.66, 1.65, 3.24, 4.85, 6.41%/m obscuration)

### Drift Compensation

High sensitivity maintenance alert signal

Low sensitivity maintenance alert signal

Maintenance urgent signal

## Accessories



M02-09-00 Test Magnet with Telescoping Handle

## System Sensor Sales and Service

### System Sensor Headquarters

3825 Ohio Avenue  
St. Charles, IL 60174  
Ph: 800-SENSOR2  
Fx: 630/377-6495  
Documents on Demand  
1-800-736-7672 x3  
www.systemsensor.com

### System Sensor Canada

Ph: 905.812.0767  
Fx: 905.812.0771

### System Sensor Europe

Ph: 44.1403.276500  
Fx: 44.1403.276501

### System Sensor in China

Ph: 86.29.524.6253  
Fx: 86.29.524.6259

### System Sensor in Singapore

Ph: 65.273.2230  
Fx: 65.273.2610

### System Sensor – Far East

Ph: 85.22.191.9003  
Fx: 85.22.736.6580

### System Sensor – Australia

Ph: 613.54.281.142  
Fx: 613.54.281.172

### System Sensor – India

Ph: 91.124.637.1770 x.2700  
Fx: 91.124.637.3118