



F100 Firmware PC Configuration Utility Reference

Head Office

Wellington

PO Box 35-063
Naenae
17 Eastern Hutt Rd
Wingate
Lower Hutt
Tel (04) 567-3229
Fax (04) 567-3644

www.pertronic.co.nz

sales@pertronic.co.nz
tech@pertronic.co.nz

Auckland Office

PO Box 15-867
New Lynn
Auckland 0640
359 Onehunga Mall
Onehunga
Auckland 1061
Tel (09) 633-0226
Fax (09) 633-0228



ISO 9001: 2000

International Standards
Certifications
QAC/R61/0051

Table 1 provides information to assist field engineers select the correct PC Configuration Utilities for New Zealand **F100** Panels.

F100 Panel	µProcessor	PCB Hardware	NZS4512	Firmware	Configuration Utility
F100A Boolean	AVR 256	v4.30 v3.11	2010 or 1997	v5.nn.nnK	v5.14.03
F100A Boolean	AVR 128	v3.01 – v3.11	2010 or 1997	v4.60.nnK to v3.nn.nnK	v3.24.n
F100A Non-Boolean	AVR 128	v2.nn	1997	v2.nn.nnK	v2.14
F100TMS	TMS	v1.nn	1997	v1.nn	v2.1

Table 1

Notes:

- 1) v5.14.03 Configuration Utility is compatible with AVR 256 firmware v5.nn.nnk only.
- 2) v3.24.n re-integrates the Configuration Utility programme and supersedes both v3.18.02 and v3.14 for all Boolean firmware from v3.nn.nnk to v4.54.nnK.
- 3) v3.24.n detects the firmware used on the **F100** Panel and can be adapted to allow access to features supported by the Panel firmware.
- 4) v3.24.n Configuration Utility is not compatible with either v2.nn.nnK Non-Boolean AVR panels, which use v2.14 Configuration Utility or v1.nn TMS panels, which use v2.1 Configuration Utility.
- 5) The AVR micro-processor (µP) is field programmable using either:
 - a. the traditional AVR Programmer software and Programming Cable using the PC's RS232 port.
 - b. the FISP4D Programmer using the PC's USB port.
- 6) The TMS micro-processor (µP) is NOT field programmable, but must be replaced with a new processor IC to upgrade the F100 firmware.

The latest Configuration Utilities and Panel Manuals are available on the Pertronic website:

<http://www.pertronic.co.nz>

Phone Pertronic Technical Support to obtain the necessary logon and password to access the files.

04 567-3229, Ext 2