

FIRE MARKET DOOR RETAINER




WMAG-DR-24
WMAG-DR-24-50
WMAG-DR-240-50



WMAG-FB

Electromagnetic Door Retainer Device. Can be used to hold open fire doors, which are then released when power to the unit is removed in the event of an alarm condition via a local relay. A matching bracket is also available to fix the door retainer to the floor.



Device Type	Magnetic Door Retainer		
Installation	INDOOR		
Ingress Protection	IP 42	IP 42	IP 42
Holding Force	200Newtons 20Kg P = 0.6 W	500Newtons 50Kg P = 1.2 W	500Newtons 50Kg P = 1.65 W
Operational Voltage	24Vdc	24Vdc	240Vac
Operating Current	25mA	45mA	7mA
Local Release Button	Yes	Yes	Yes
	Order Code		
Door Retainer	WMAG-DR-24	WMAG-DR-24-50	WMAG-DR-240-50
Bracket	WMAG-FB		

E. & O.E.

Document Ref.
LIT:180
November 2001

